



## DMX-4

It's a 4-channel dimmer/relay pack providing DMX control for on/off or dimming to units not equipped with DMX on their own. The fixture is optimized for use with small LED fixtures to prevent ghosting and flickering. Each of the 4 sets of outlets (duplex) can be set to any DMX address and independently set as a dimmer or relay. Sixteen user-selectable chase patterns make programming a breeze.

# Highlights

- 4-channel dimmer/switch pack with up to 5 amps per channel (15A max)
- Auto on/off when DMX is detected or removed
- Provides DMX control for on/off or dimming to non-DMX fixtures
- Built in circuitry generates a phantom load to prevent ghosting and flickering in LED fixtures
- Custom looks at your fingertips with 16 built-in, configurable chases
- Easy control using standalone mode or DMX control
- Increase flexibility by setting each channel as a dimmer or switch
- Control up to eight units simultaneously with four duplex outlets
- Monitor the status of each channel with separate LED indicators
- Generate a synchronized show using easily accessible automated programs, built-in automated programs
- Great control without DMX using automated programs with adjustable speeds and dimmer levels

## Specifications

- DMX Channels: 1, 2, or 4
- DMX Connectors: 3-pin XLR
- Input Voltage: 100 to 240 VAC, 50/60 Hz (auto-ranging)
- Weight: 5 lb (2.2 kg)
- Dimensions: 8.3 x 7.7 x 2.8 in (210 x 194 x 70 mm)
- Approvals: CE

## What's Included

- Power cord
- Warranty card