



FlareCON Air

The FlareCON Air utilizes cell phones and tablets and turns them into wireless DMX controllers. It works with all CHAUVET DJ [Freedom](#) series fixtures as well as all D-Fi products for versatile control over your rig.

The built-in Wi-Fi transmitter connects with cell phones and tablets running the FREE FlareCON app, to allow the user to control the connected lighting fixtures. The FlareCON Air then converts the Wi-Fi signal from the phone or tablet into D-Fi and wirelessly transmits those signals to an unlimited number of receivers.

The FlareCON app is available for both Android and iOS® in both phone and tablet versions. The FlareCON Air can also connect directly to a DMX controller to send wireless signals out to an unlimited number of D-Fi lights or receivers.

Download Here: [Android](#) | [iOS](#)

The FlareCON Air is fully FCC and RTTE compliant.



Highlights

- FlareCON™ App is now available for download: [Android](#) | [iOS](#)
- Compact, easy-to-use Wi-Fi receiver and wireless D-Fi transmitter in a single unit
- Compatible with Android™ operating system and Mac OS® on both smartphones and tablets
- Output can be used in wireless D-Fi and/or wired DMX protocols
- Wirelessly synchronize an unlimited number of D-Fi-ready fixtures and receivers simultaneously
- Built-in options include manual or automatic channel selection
- Simple navigation and text readout using the OLED digital display
- Mounting options include built-in hook and loop fastener strap, keyhole mounting holes, M10 and M12 threaded holes for direct mounting to truss
- Fully FCC/RTTE compliant

Specifications

- DMX Channels: 512
- DMX Connectors: 3-pin XLR
- Input Voltage: 9 VDC, 500 mA (external power supply: 100 to 240 VAC, 50/60 Hz)
- Power and Current: 4 W, 0.1 A @ 120 V, 60 Hz
4 W, 0.1 A @ 230 V, 50 Hz
- Weight: 1.2 lb (0.6 kg)
- Size: 5.59 x 3.58 x 1.81 in (142 x 91 x 46 mm)
- Approvals: CE, FCC

What's Included

- External Power Supply
- Warranty Card
- Stickers