

Software Upload Instructions

1. Download ZIP file onto USB thumb drive from web page and extract the contents.
2. Create a folder in the root directory and name it "Intimidator Beam Q60" (must be named exactly this).
3. Paste the contents of the ZIP file within this folder.
4. Power on the fixture and let it boot.
5. Go to "SYSINFO" on the main menu and note the current firmware version.
6. Insert the USB drive into the USB-C port on the rear.
7. Put an "*" next to each of the 3 files by pressing enter. Once all 3 files have an "*" select the "yes" menu option.
8. The fixture will now update its firmware and reset automatically.
9. While the unit is resetting, remove the USB thumb drive.
10. After resetting, confirm the files were successfully updated from the "SYSINFO" icon on the main menu.

Notes

- The USB thumb drive must be formatted to exFAT32.
- Up to 8 fixtures can be daisy chained using a standard DMX cable to update simultaneously.