

FlareCON Air 2

HIGHLIGHTS

- Compact, 100% TRUE wireless Wi-Fi™ receiver and wireless D-Fi™ transmitter in a single unit
- Save time running cables with the built-in battery
- Generates its own Wi-Fi™ network and can be used anywhere with no internet or hotspot needed
- Compatible with both [Android™](#) and [Apple®](#) operating systems for smartphones and tablets
- Can control non-D-Fi™-enabled fixtures using the included cable adapter
- Wirelessly control an unlimited number of D-Fi™-ready fixtures and receivers simultaneously
- Simple navigation and text readout using the OLED digital display
- Built-in hook and loop fastener for direct mounting to truss
- Fully FCC/RTTE compliant



SPECIFICATIONS

- DMX Channels : 512
- DMX Connectors : 3-pin XLR
- Max Unobstructed Distance : (Wi-Fi™): 100 ft (30.5 m)
(D-Fi™): 600 ft (183 m)
- Maximum Run Time : up to 8 hours
- Recharge Time : 4 hours
- Operating Frequency : 2.412 to 2.484 GHz
- Antenna Connection : RP-SMA
- Input Voltage : 5 VDC, 1.6 A (external power supply: 100 to 240 VAC, 50/60 Hz)
- Power and Current : 4 W, 0.72 A @ 120 V, 60 Hz
4 W, 0.45 A @ 230 V, 50 Hz
- Weight : Weight: 0.6 lb (0.3 kg)
- Size : 6.2 x 3.3 x 0.9 in (158 x 83 x 24 mm)
- Approvals : CE, FCC

WHAT'S INCLUDED

- FlareCON Air 2
- External Power supply
- USB cable
- DMX adaptor
- Quick Reference Guide