

Timer System Package

HIGHLIGHTS

- Convenient pack includes: double space (2U) mounting rack, 8-channel relay pack (SR-8) and 25 ft (SF-EXCB) linking cable
- Individual control of 2 separate zones with 4 channels each (8 channels total)
- Each zone contains: 4 channels with LED indicator and flash button, separate blackout button, selector switch for automatic or sound-activated programs; speed control knob for automatic programs (20 sec – 15 min)
- Compatible with external 16-pattern controller (CH-866, sold separately)
- Connect up to 2 relay packs together (SR-8, sold separately)
- Increase effects with fog and adjustable strobe speed control buttons
- Non-switched output for linking relay packs (on SR-8)



SPECIFICATIONS

- Input Voltage : (controller): 120/230 VAC, 50/60 Hz (switchable)
(relay pack): 100 to 240 VAC, 50/60 Hz (auto-ranging)
- Power and Current : (controller): 1 W, 0.1 A @ 120 V, 60 Hz
(controller): 1 W, 0.1 A @ 230 V, 50 Hz
- Weight : (controller): 4.6 lb (2.1 kg)
(relay pack): 2.5 lb (1.3 kg)
- Size : (controller): 19 x 3.5 x 3.7 in (482 x 88 x 94 mm)
(relay pack): 14 x 3.8 x 1.8 in (356 x 97 x 46 mm)
- Approvals : CE
- Output : (relay pack 120 V): 5 A (575 W) per channel, 15 A (1,725 W) max
(relay pack 230 V): 5 A (1,150 W) per channel, 15 A (3,450 W) max
- Rackmount : (controller): 2U

WHAT'S INCLUDED

- SR-8 relay pack
- SF-EXCB extension cable
- User Guide
- Warranty card