



D-Fi Rx 2.4

D-Fi Rx 2.4 is the latest addition to the D-Fi family of easy to use, wireless DMX units. The super-compact Rx model acts solely as a receiver for any product that transmits the D-Fi 2.4GHz signal including: [D-Fi Tx 2.4](#), [D-Fi 2.4GHz](#) and Freedom Series. For more stable communication between units, this version operates on a 2.4 GHz frequency range and includes an “auto” function which automatically finds the best frequency available and effortlessly syncs the units.



Highlights

- Compact, easy-to-use wireless DMX receiver
- Achieve up to 656 ft of wireless DMX communication (clear line of sight)
- Compatible with all CHAUVET® DJ D-Fi™ 2.4 GHz products
- Wirelessly synchronize multiple receivers to a single CHAUVET® DJ D-Fi™ 2.4 GHz transmitter
- Quickly and easily synchronize with the press of a button
- Adjustable antenna includes a safety transport clip
- Mounting options include teardrop holes for wall mounting and an M12 threaded hole for a clamp

Specifications

- DMX Connectors: 3-pin XLR
- Max Unobstructed Distance: 656 ft (200 m)
- Operating Frequency: 2.433 to 2.481 GHz
- Input Voltage: 9 VDC, 500 mA (external power supply: 100 to 240 VAC, 50/60 Hz)
- Weight: 0.4 lb (0.18 kg)
- Dimensions: 3.8 x 2.6 x 1.5 in (97 x 66 x 38 mm)
- Approvals: CE, FCC
- RF output: 18.5 dBm
- Antenna Connection: RP-SMA

What's Included