



## DMX-RT

DMX-RT is a rugged and compact DMX recording device with triggerable playback from DMX or the phoenix connectors. Copy, backup and transfer show files with a micro SD card (not included). The unit comes with a mounting bracket for convenient mounting options. The digital display is easy to navigate and lets you easily trigger scenes.



# Highlights

- DMX recording device with triggerable playback from DMX or the phoenix connectors
- Normally Open (N/O) or Normally Closed (N/C) triggers allow the use of most common sensors
- Easily navigate and trigger scene using the digital display
- Copy, backup and transfer show files with a micro SD card (not included)
- Integrated mounting bracket to quickly install into any location.
- Supplies DC voltage through terminal block to power specific triggers

## Specifications

- DMX Connectors: 3-pin XLR
- Input Voltage: 12 VDC, 1 A (external power supply: 100 to 240 VAC, 50/60 Hz)
- Power and Current: 1 W, 0.03 A @ 120 V, 60 Hz  
1 W, 0.03 A @ 230 V, 50 Hz
- Weight: 0.4 lb (0.2 kg)
- Size: 3 x 2.9 x 1.7 in (77 x 73 x 43 mm)
- Approvals: CE
- Programmable Scenes: 999
- Trigger Type: N/O or N/C
- Terminal Block output: 12 VDC, 100 mA
- Micro SD: 32 GB  
Speed: Class 10 (or higher)  
Format: FAT32

## What's Included

- Power adapter
- Warranty card
- Quick Reference Guide