



# Obey 40

The Obey 40 is the next step up from the Obey 10, allowing for control of up to 12 fixtures at 16 channels each. With a slightly larger size comes a larger capacity: the Obey 40 has 30 banks on 8 scenes, or up to 240 scenes. The Obey 40 offers the flexibility of its little brother but also adds fog and strobe control and MIDI compatibility.



# Highlights

- Universal DMX controller capable of handling all the complexities of today's lighting fixtures
- Easily control up to 12 intelligent lights with up to 16 channels each
- Includes 192 channels of DMX control and 30 banks of 8 scenes for a maximum of 240 scenes
- Enhance light shows with 6 sets of chase effects containing 240 scenes
- Increase effects with fog and strobe control, beat activation, tap-sync and auto run
- Capability to grab any fixture on the fly and sequentially link chases
- Increase flexibility with MIDI compatibility and DMX polarity selector
- Conveniently mounts using the 3-space (3U) mounting rack

## Specifications

- DMX Channels: 192
- DMX Connectors: 3-pin XLR
- Rackmount: 3U
- Input Voltage: 9 VDC, 500 mA (external power supply: 100 to 240 VAC, 50/60 Hz)
- Weight: 5.7 lb (2.6 kg)
- Size: 19 x 3.5 x 6.7 in (483 x 89 x 171 mm)
- Approvals: CE

## What's Included

- External power supply
- Quick Reference Guide
- Warranty card