



Wash FX Hex

Brilliance, brightness and versatility are packed inside this powerhouse multi-purpose effect light that packs a punch with hex color (RGBAW+UV) LEDs. Wash FX Hex functions as a chase effect, blinder, or a wash light. 6 chasing zones mean Wash FX Hex can be used as a regular wash light or eye-candy effect and an advanced master/slave feature that allows you to mirror effects between units. Multiple control options include stand-alone mode, DMX, and IR as Wash FX Hex is compatible with an optional [IRC-6](#) wireless remote for wireless triggering. Power linking saves time running cables. Fits best in the [CHS-40 VIP gear bag](#).



Highlights

- Multi-purpose effect light functions as chase effect, blinder, or a wash light
- Generate a broad spectrum of colors and achieve natural-looking color temperatures with Hex color LEDs
- Advanced master/slave feature allows you to mirror effect between units
- Use as a regular wash light or eye-candy effect with 6 chasing zones
- Multiple control options include stand-alone, DMX, IR, or master/slave
- Compatible with the IRC6 wireless remote for wireless triggering
- Power linking saves time running cables
- Fits best in the CHS-40 VIP gear bag

Specifications

- DMX Channels: 3, 6, 11 or 40
- DMX Connectors: 3-pin XLR
- Light Source: 18 LEDs (hex-color RGBAW+UV) 8 W, 2.8 A, 50,000 hours life expectancy
- Strobe Rate: 0 to 24 Hz
- Beam Angle: 41°
- Field Angle: 68°
- Illuminance: 2,422 lux @ 2 m
- Power Linking: 3 units @ 120 V; 5 units @ 230 V
- Input Voltage: 100 to 240 VAC, 50/60 Hz (auto-ranging)
- Power and Current: 200 W, 2.5 A @ 120 V, 60 Hz
194 W, 1.5 A @ 230 V, 50 Hz
- Weight: 7.0 lbs (3.2 kg)
- Size: 11.2 x 6.3 x 13 in (285 x 160x 330 mm)
- Approvals: CE
- Optional Controllers: IRC-6
- Wavelength: 380 to 400 nm

What's Included

- Wash FX Hex
- Power Cable
- Quick Reference Guide