## COLORband H9 ILS

## HIGHLIGHTS

- Full-size hex-color LED strip light functions as chase effect, blinder, or wall washer
- Built-in RF receiver compatible with the optional RFC and • **RFC-XL** remotes
- ILS compatibility for use in the ILS ecosystem
- D-Fi USB compatibility for wireless Master/Slave or DMX control (D-Fi™ USB sold separately) .
- Generate a broad spectrum of colors and achieve naturallooking color temperatures with 6-in-1 LED technology
- 3 zones of control create amazing chase effects
- Convenient access to multiple prebuilt programs with or without DMX
- Includes multiple DMX personalities for a wide variety of programming styles
- Ideal for quiet applications due to silent operation and no moving parts
- Easily transports in the optional CHS-60 VIP gear bag

## SPECIFICATIONS

- DMX Channels : 6, 9, 11, 18, 23 DMX Connectors : 3- and 5-pin XLR Light Source : 9 LEDs (Hex-color RGBWA+UV 10W (1.09A • 50,000 hours life expectancy
- Strobe Rate : 0 to 16 Hz
- Beam Angle : 23°
- Field Angle : 41° Illuminance : 3,529 lux @ 2 m Lumens : 2,977
- •
- Power and Current : 80 W, 1.1 A @ 120 V, 60 Hz
- .
- 79 W, 0.6 A @ 230 V, 50 Hz Weight : 7.2 lbs (3.3 kg)
- Size : 39.4 x 2.2 x 6.8 in (1000 x 56 x 172 mm)
- Approvals : CE, UKCA, RoHS, MET Optional Controllers : RFC, RFC-XL, D-Fi USB

## WHAT'S INCLUDED

- COLORband H9 ILS
- Power cord
- Hanging bracket ٠
- Quick Reference Guide



