

# DMX-RT4

## HIGHLIGHTS

- DMX recording and playback device with 4 independent triggers
- Each trigger can be programmed and triggered separately
- Copy, backup and transfer show files using the USB-C connector
- Standard headphone connector (3.5mm) connects to external audio systems for amplified playback
- Password protection ensures shows will not be altered
- Normally Open (N/O) or Normally Closed (N/C) triggers allow the use of most common sensors
- Supplies DC voltage through terminal block to power specific triggers



## SPECIFICATIONS

- DMX Channels : 3-pin XLR
- Input Voltage : 12 VDC, 1 A (external power supply: 100 to 240 VAC, 50/60 Hz)
- Power and Current :  
1 W, 0.03 A @ 120 V, 60 Hz  
1 W, 0.03 A @ 230 V, 50 Hz
- Weight : 0.4 lb (0.2 kg)
- Size : 4.8 x 3.2 x 1.5 in (122 x 81 x 38 mm)
- Approvals : CE, UKCA, RoHS
- Compatible audio formats : MP3 (32-320kbps), WAV (8 or 16bit only)
- Onboard memory : 32 GB
- Filename max length (MP3/WAV) : 12 characters
- Filename max length (show file) : 11 characters
- Trigger Type : auto, toggle, N/O or N/C
- Terminal Block output : 12 VDC, 100 mA

## WHAT'S INCLUDED

- DMX-RT4
- External power supply
- Quick Reference Guide