

Freedom H1

HIGHLIGHTS

- 100% TRUE wireless, battery-operated, LED wash with built-in D-Fi transceiver
- System includes 4 fixtures, 4 diffusers, a carry bag, multi-charger and [IRC-6](#) remote
- Quick swapping of filters and gradients with the included magnetic gel holder
- Multiple control options include stand-alone, wireless DMX or IR
- Compact size provides effortless transport and set-up
- Digital display for easy control and adjusting all settings
- Magnetic base to easily mount light to most metal surfaces
- Built-in Kensington security slot prevents theft



SPECIFICATIONS

- DMX Channels : 6, 8 or 12
- Light Source : 1 LED (hex-color RGBAW+UV) 10W, (3 A), 50,000 hours life expectancy
- Strobe Rate : 0 to 25 Hz
- Beam Angle : 21°
- Field Angle : 32°
- Operating Frequency : 2.412 to 2.484 GHz
- Illuminance : (w/ filter): 268 lux @ 2 m
(w/o filter): 314 lux @ 2 m
- Input Voltage : 8.4VDC, 1.5A (external power supply: 100-240 VAC, 50/60 Hz)
- Weight : 1.4 lb (0.7 kg)
- Size : 3.8 x 3 x 8.5 in (97 x 75 x 139 mm)
- Approvals : CE, FCC
- Maximum Run Time (all on) : up to 8 hours
- Maximum Run Time (single color) : up to 20 hours
- Recharge Time : 7 hours
- Bracket Mounting Hole : M12

WHAT'S INCLUDED

- 4x Freedom H1
- 4x diffusers
- Multi charger
- IRC-6
- Carry bag