## Freedom Par Hex-4

## **HIGHLIGHTS**

- 100% TRUE wireless, battery-operated, hex-color (RGBAW+UV) LED Par with built-in D-Fi™ transceiver
- Multiple wireless triggering and control options via the FlareCON™ Air and the FlareCON™ app
- Works in Master/Slave with first-generation Freedom™
- Shine light where it is needed using the built-in adjustable kickstand
- Built-in glare shield prevents light spillage Extend the battery's lifespan with built-in discharge
- Convenient, wireless non-DMX control using the IRC-6 remote
- Create customized colors using the built-in LED display
- Achieve smooth LED fading with built-in dimming curves
- Safely store and transport your fixtures from gig to gig in the CHS-FR4 carry bag
  Compact and lightweight design easily fits inside sticks of
- **TRUSST®**
- Increase battery run time with built-in limiter circuitry that conserves energy when over 4 colors are in use simultaneously



## **SPECIFICATIONS**

- DMX Channels : 6, 8, or 12 DMX Connectors : 3-pin XLR
- Light Source: 4 LEDs (hex-color RGBAW+UV) 10 W (2 A), 50,000 hours life expectancy
- Strobe Rate: 0 to 25 Hz PWM Frequency: 1,200 Hz Beam Angle: 23°
- Field Angle: 34°
- Maximum Run Time: (all on): up to 8 hours (with limiter on)
  - (single color): up to 20 hours Recharge Time: 6 hours
- Operating Frequency : 2.412 to 2.484 GHz Illuminance : 1,372 lux @ 2 m
- Power Linking: 26 units @ 120 V; 50 units @ 230 V Input Voltage: 100 to 240 VAC, 50/60 Hz (auto-ranging) Power and Current: 35 W, 0.3 A @ 120 V, 60 Hz 34 W, 0.2 A @ 230 V, 50 Hz Weight: 6.2 lb (2.9 kg)

- Size : 5.4 x 5.7 x 7.2 in (138 x 145 x 184 mm) Approvals : CE, FCC

## WHAT'S INCLUDED

- IRC-6
- Power Cord
- Quick Reference Guide
- Warranty Card
- Stickers

