

Freedom Stick X4

HIGHLIGHTS

- Unique and versatile free-standing LED array that adds pizzazz to any event
- Slip on frosted tubes allow for 2 completely different looks
- Half of the stick can be deactivated to provide a 180° effect saving battery life
- Built-in 3-pin DMX connectors make control compatible with other DMX enabled fixtures
- Control auto and sound programs via DMX, wireless master/slave, or the included RFC remote
- Optional RFC-XL remote allows grouping of several sets of Freedom Sticks without DMX.
- Battery-powered and built-in D-Fi receiver allows the stick to be placed anywhere
- Each LED can be pixel-mapped for ultimate show and programming creativity
- Detachable metal base allows for truss mounting (clamps sold separately)
- User-customizable automated programs create complex looks in seconds



SPECIFICATIONS

- DMX Channels : 3, 8, 48, 50
- DMX Connectors : 3-pin XLR
- Max Unobstructed Distance : 600 ft (183 m)
- Light Source : 32 LEDs (tri-color RGB) 0.2 W, (12 mA), 50,000 hours life expectancy
- Strobe Rate : 0 to 30 Hz
- Maximum Run Time :
Maximum Run Time (360°): 5 hours Maximum Run Time
(180°): 10 hours Maximum Run Time
(single color): 20 hours
- Recharge Time : 4 hours
- Input Voltage : external power supply: 100 to 240 VAC, 50/60 Hz
- Power and Current :
11 W, 0.1 A @ 120 V, 60 Hz
11 W, 0.1 A @ 230 V, 50 Hz
- Weight : 3.3 lbs. (1.5 kg)
- Size :
Size (fixture): 59 x 6.3 x 6.3 in (1500 x 160 x 160 mm)
Size (carry bag): 61 x 10.6 x 2.6 in (1550 x 270 x 65 mm)
- Approvals : CE, UKCA, RoHS, FCC
- Operating Frequency : 2.412 to 2.484 GHz
- Bracket Mounting Hole : M10
- Optional Controllers : RFC-XL, FlareCON

WHAT'S INCLUDED

- 4 Freedom sticks
- 4 Diffusion tubes
- 4 USB charging cables
- Multi-Charger
- RFC remote
- Carry bag
- Quick Reference Guide