

# Shocker FX

Punch up a stunning eye candy effect as easily as picking a strobe, wash, or blinder look, all with the press of a button. This compact party strobe combines built-in effect presets with eight sections of bright RGB color and four sections of intense cool white LEDs to deliver instant visual impact. Event managers and entertainers alike will enjoy the high output, fast transitions, and secure setups this versatile showstopper brings to the party.

## HIGHLIGHTS

- Versatile blinder, wash and strobe light with brilliant eye candy effects
- 12 controllable sections (8 RGB + 4 white) allow for creative programming flexibility
- Trigger eye-catching effects with built-in automated programs via Master/Slave, DMX mode or optional IRC-6 remote
- Combine zone control and special effect macros for stunning visual impact
- Save time running cables and extension cords by power linking multiple units
- Easily transports in the optional CHS-25 VIP gear bag



## SPECIFICATIONS

- DMX Channels : 8, 18, 30, or 43
- DMX Connectors : 3-pin XLR
- Light Source : 280 LEDs (tri-color) 50 W, (1.5 A), 50,000 hours life expectancy
- Strobe Rate : 0 to 20 Hz
- Beam Angle : 97°
- Field Angle : 139°
- Illuminance : 219 lux @ 2 m
- Lumens : 1,981
- Power Linking : 12 units @ 120 V; 20 units @ 230 V
- Input Voltage : 100 to 240 VAC, 50/60 Hz (auto-ranging)
- Power and Current : 45 W, 0.4 A @ 230 V, 50 Hz
- Weight : 2.0 lb (1.0 kg)
- Size : 10.2 x 3.25 x 5.1 in (260 x 82.6 x 129 mm)
- Approvals : CE, ROHS
- Light Source : 56 LEDs (cool white), 11 W (.8 A), 50,000 hours life expectancy
- Power and Current : 45 W, 0.6 A @ 120 V, 60 Hz

## WHAT'S INCLUDED

- Shocker FX
- Power cord
- QRG